



**GAS JANITOR**  
a true safety

## GAS LEAKAGE ALARM PANEL-8 ZONE

### Description:

The **GJCP-08** is an 8-Zone control panel. It shows current status of all connected gas leak detectors. Detectors and control panel connected with four core cable. And it is the central part of conventional gas leakage alarm system. This control panel is also compatible with operate solenoid valve, Hooter, Siren, Fire Panel and BMS.



### Features:

- 16x2 dot matrix LCD display
- Zone wise LED's indications  
**HEALTHY/ NORMAL: GREEN LED & GAS LEAKAGE: RED LED**
- PFC for fire panel communication or other actuators
- External TEST switches of manual testing of each zones
- External switches for RESET control panel and Hooter SILENCE
- Mains ON, System ON, Common LEAKAGE, SILENCE all have seprate LED indications.
- Three Layer High voltage/current protection.
- Esay Installation i.e. close to PLUG & PLAY type
- Battery Back up also available(Optional)

# TECHNICAL DATA SHEET



**GAS JANITOR**  
a true safety

## Technical Specifications:

- Operating Voltage : 220VAC±20
- Temperature : 0 to 55°C
- Humidity : 95% (Non-Condensing)
- Output 1 : 24 VDC 1.5 Amp for Solenoid Valve
- Output 2 : 24 VDC 1 Amp for Hooter
- Output 3 : PFC for Actuators
- Dimensions : (L)330mm\*(W)230mm\*(D)100mm
- Color : Caramel White
- Material : CRCA Sheet GAUGE 20 & dual powder coated

## Structure Dimensions:

